



EV & Forklift Parts

CURTIS DC Motor Controller Parameter List
Model: 1215-8307

No.	Parameter	Min	Max	Default Value	Unit	Programmer Access Level	
						Read	Write
1	EMR REV C/L	20	500	20	Ampere	OEM	OEM
2	THROTTLE TYPE	1	3	2	#	OEM	OEM
3	RAMP SHAPE	20	70	20		OEM	OEM
4	CREEP SPEED	0	25	4	%	User	User
5	EMR REV SPEED	25	100	25	%	OEM	OEM
6	SEQUENCING DLY	0	3	0.4	Seconds	OEM	OEM
7	VARIABLE PLUG	Off	On	On		OEM	OEM
8	HIGH PEDAL DIS	0	2	2	#	OEM	OEM
9	SRO	0	3	0	#	OEM	OEM
10	ANTI-TIEDOWN	Off	On	Off		OEM	OEM
11	QUICK START	0	6	1.6		OEM	OEM
12	M1 MAIN C/L	20	500	500	Ampere	OEM	OEM
13	M1 PLUG C/L	20	500	195	Ampere	User	User
14	M1 RAMP C/L	20	500	250	Ampere	OEM	OEM
15	M1 ACCEL RATE	0	3	3	Seconds	User	User
16	M1 MAX SPEED	40	100	100	%	OEM	OEM
17	M2 MAIN C/L	20	500	500	Ampere	OEM	OEM
18	M2 PLUG C/L	20	500	195	Ampere	User	User
19	M2 RAMP C/L	20	500	250	Ampere	OEM	OEM
20	M2 ACCEL RATE	0	3	3	Seconds	User	User
21	M2 MAX SPEED	40	100	100	%	User	User
22	NEUT BRAKE C/L	10	500	10	Ampere	OEM	OEM
23	NEUTRAL BRAKE	Off	On	Off		OEM	OEM

NEW OCEAN TECHNOLOGY CO., LTD.

Website: <https://www.noco-evco.com/> - Email: info@noco-evco.com