



EV & Forklift Parts

CURTIS DC Series & Compound Motor Controller Parameter List
Model: 1207B-5101

No.	Parameter	Min	Max	Default Value	Unit	Programmer Access Level	
						Read	Write
1	EMR Rev C/L	20	300	140	Ampere	OEM	OEM
2	Throttle Type	1	3	2		OEM	OEM
3	Ramp Shape	20	70	50		OEM	OEM
4	Creep Speed	0	25	5	%	User	User
5	EMR Rev Speed	25	100	60	%	OEM	OEM
6	Sequencing DLY	0	3	0	Seconds	OEM	OEM
7	Variable Plug	Off	On	On		OEM	OEM
8	High Pedal Dis	0	2	0		OEM	OEM
9	SRO	0	3	1		OEM	OEM
10	Anti-Tiedown	Off	On	Off		OEM	OEM
11	Quick Start	0	6	1.4		OEM	OEM
12	M1 Main C/L	20	300	300	Ampere	OEM	OEM
13	M1 Plug C/L	20	300	70	Ampere	User	User
14	M1 Ramp C/L	20	300	100	Ampere	OEM	OEM
15	M1 Accel Rate	0	3	1	Seconds	User	User
16	M1 Max Speed	40	100	100	%	OEM	OEM
17	M2 Main C/L	20	300	250	Ampere	OEM	OEM
18	M2 Plug C/L	20	300	70	Ampere	User	User
19	M2 Ramp C/L	20	300	100	Ampere	OEM	OEM
20	M2 Accel Rate	0	3	1	Seconds	User	User
21	M2 Max Speed	40	100	60	%	User	User
22	Neut Brake C/L	10	300	70	Ampere	OEM	OEM
23	Neutral Brake	Off	On	Off		OEM	OEM

NEW OCEAN TECHNOLOGY CO., LTD.

Website: <https://www.noco-evco.com/> - Email: info@noco-evco.com